

KEY FEATURES

Battery fast-charge bays

More connections, greater connectivity

Connect to an external monitor

Ethernet

Charges while you work

THE TRIMBLE YUMA DOCKING STATION ENABLES CONVENIENT AND EFFICIENT TRANSITION BETWEEN FIELD AND OFFICE

SEAMLESSLY MOVE FROM FIELD TO OFFICE AND BACK AGAIN

The Trimble® Yuma™ Rugged Tablet docking station works just like a docking station for a conventional laptop. Simply place the Yuma rugged tablet onto the docking station and immediately experience all-in-one connectivity to your monitor, mouse, keyboard, printer and network. No hassles.

FASTER, MORE CONVENIENT BATTERY CHARGING

The Trimble Yuma docking station features an external two-bay battery charger. This enhancement lets you charge four batteries at one time. Batteries charged in the external bays charge twice as fast as those charged on the Trimble Yuma tablet.

MORE CONNECTIONS, GREATER CONNECTIVITY

Placing the Trimble Yuma rugged tablet in the docking station provides even more external connections for greater, more flexible connectivity. It offers four USB ports, a serial port, an Ethernet port, and a VGA pass-through port.

Use the VGA port for connecting to an external monitor or projector for presentations. Connect to a secure network and multiple accessories such as DVD drives and external hard drives via USB. With the Trimble Yuma docking station you're unlikely to run out of connection options, whatever your office demands.



The Trimble Yuma rugged tablet and docking station provide everything you need to get the job done right.

TRIMBLE YUMA DOCKING STATION



TECHNICAL SPECIFICATIONS

HARDWARE

Approximate Charge Times

- Two extended batteries in Dual Battery Charging Bay – 3.5 hours
- Two standard batteries on Yuma (powered off) in docking station – 5.5 hours

I/O PORTS

	Qty
USB 2.0	4
RJ45 / Ethernet	1
Headphone/Speaker Mini-Jack	1
Analog VGA Port	1
RS-232 / Serial	1
Dual Battery Charging Bay	2
Stylus Holder	1
DC Power Input	1

POWER

Wattage	90 W
Output Voltage	19 V

LED INDICATORS


Docking Station Power "Trimble" LED	
with power	Blue
without power	off
Tablet Status LED	
Tablet properly seated and powered on (including sleep mode)	Green
all other conditions	off
Battery Charging LED (x2)	
with power, charging	Amber
with power, Battery Full	Green
with power, Battery Error	Flash Amber
with power, no battery pack connected	off
without power	off

ENVIRONMENTAL

Charging temperature	0 °C to 40 °C (32 °F to 104 °F)
Humidity	95% RH, non-condensing
Water	Safe to dock tablet damp with condensation**

CERTIFICATIONS

CE, FCC, C-TICK, RoHS Compliant



- | | |
|-----------------------------|----------------------|
| 1 Dual Battery charging bay | 7 DC Power Input |
| 2 Ethernet (RJ45) | 8 Tablet Status LED |
| 3 Headphone Mini-Jack Out | 9 Dock Power LED |
| 4 VGA port (HD-5) | 10 Battery Right LED |
| 5 Serial (RS-232) | 11 Battery Left LED |
| 6 USB 2.0 (x2) | 12 USB 2.0 (x2) |

© 2009, Trimble Navigation Limited. Trimble Navigation Limited. All rights reserved. Trimble and the Globe & Triangle logo are trademarks of Trimble Navigation Limited registered in the United States and in other countries. Yuma is a trademark of Trimble Navigation Limited. All other brand names and trademarks are property of their owners. Color display images shown may vary slightly from actual display. PN 022490-070A (11/09)

* Image shows batteries seated in charging bays.

** Docking station is not water proof and should not be submerged or used outdoors in rain or snow.

TRIMBLE AUTHORIZED DISTRIBUTION PARTNER

TRIMBLE NAVIGATION LIMITED

P.O. Box 947
Corvallis, OR 97339
USA
541-750-9200 Phone
www.trimble.com/rugged
www.outdoorugged.com



www.trimble.com